

## SECTION 260923

### LIGHTING CONTROL DEVICES

#### PART 1 - GENERAL

##### 1.1 STIPULATIONS

- A. The specification sections “General Conditions of the Construction Contract”, “Special Conditions”, and “Division 1 - General Requirements” form a part of this section by this reference thereto, and shall have the same force and effect as if printed herewith in full.

##### 1.2 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

##### 1.3 SUMMARY

- A. Section Includes:

- 1. Time switches.
- 2. Photoelectric switches.
- 3. Digital timer light switches.
- 4. Lighting contactors.

- B. Related Requirements:

- 1. Section 262726 "Wiring Devices" for wall-box dimmers, non-networkable wall-switch occupancy sensors, and manual light switches.

##### 1.4 ACTION SUBMITTALS

- A. Product Data: For each type of product.

- B. Shop Drawings:

- 1. Show installation details for the following:
  - a. Occupancy sensors.
  - b. Vacancy sensors.
- 2. Interconnection diagrams showing field-installed wiring.
- 3. Include diagrams for power, signal, and control wiring.

- C. Field quality-control reports.

- D. Sample Warranty: For manufacturer's warranties.

## 1.5 CLOSEOUT SUBMITTALS

- A. Operation and Maintenance Data: For each type of lighting control device to include in operation and maintenance manuals.

## 1.6 WARRANTY

- A. Manufacturer's Warranty: Manufacturer and Installer agree to repair or replace lighting control devices that fail(s) in materials or workmanship within specified warranty period.
  - 1. Failures include, but are not limited to, the following:
    - a. Faulty operation of lighting control devices.
  - 2. Warranty Period: Two year(s) from date of Substantial Completion.

## PART 2 - PRODUCTS

### 2.1 TIME SWITCHES

- A. Electronic Time Switches: Solid state, programmable, with alphanumeric display; complying with UL 917.
  - 1. Listed and labeled as defined in NFPA 70 and marked for intended location and application.
  - 2. Contact Configuration: DPST.
  - 3. Contact Rating: 30-A inductive or resistive, 240-V ac.
  - 4. Programs: Two on-off set points on a 24-hour schedule, allowing different set points for each day of the week and an annual holiday schedule that overrides the weekly operation on holidays.
  - 5. Circuitry: Allow connection of a photoelectric relay as substitute for on-off function of a program on selected channels.
  - 6. Astronomic Time: All channels.
  - 7. Automatic daylight savings time changeover.
  - 8. Battery Backup: Not less than seven days reserve, to maintain schedules and time clock.

### 2.2 OUTDOOR PHOTOELECTRIC SWITCHES

- A. Description: Solid state, with SPST dry contacts rated for 1800 VA inductive, to operate connected relay, contactor coils, or microprocessor input; complying with UL 773A, and compatible with ballasts and LED lamps.
  - 1. Listed and labeled as defined in NFPA 70, by a qualified testing agency, and marked for intended location and application.

2. Light-Level Monitoring Range: 1.5 to 10 fc, with an adjustment for turn-on and turn-off levels within that range, and a directional lens in front of the photocell to prevent fixed light sources from causing turn-off.
3. Time Delay: Fifteen-second minimum, to prevent false operation.
4. Surge Protection: Metal-oxide varistor.
5. Mounting: Twist lock complies with NEMA C136.10, with base-and-stem mounting or stem-and-swivel mounting accessories as required to direct sensor to the north sky exposure.
6. Failure Mode: Luminaire stays ON.

## 2.3 DIGITAL TIMER LIGHT SWITCH

- A. Description: Combination digital timer and conventional switch lighting control unit. Switchbox-mounted, backlit LCD display, with selectable time interval in preset intervals. The unit shall have no hold feature.
  1. Rated 960 W at 120-V ac for tungsten lighting, 10 A at 120-V ac or 10 amps at 277-V ac for LED, and 1/4 horsepower at 120-V ac.
  2. Voltage: Dual voltage - 120 and 277 V.
  3. Color: White.
  4. Faceplate: Color matched to switch unless a standard device plate can be used. Then it shall match all others in material and finish.

## 2.4 LIGHTING CONTACTORS

- A. Description: Electrically operated and electrically held (unless noted otherwise), combination-type lighting contactors with fusible switch, complying with NEMA ICS 2 and UL 508.
  1. Current Rating for Switching: Listing or rating consistent with type of load served, including tungsten filament, inductive, and high-inrush ballast (ballast with 15 percent or less THD of normal load current).
  2. Fault Current Withstand Rating: Equal to or exceeding the available fault current at the point of installation.
  3. Enclosure: Comply with NEMA 250.
  4. Provide with control and pilot devices as indicated on Drawings, matching the NEMA type specified for the enclosure.

## PART 3 - EXECUTION

### 3.1 EXAMINATION

- A. Examine lighting control devices before installation. Reject lighting control devices that are wet, moisture damaged, or mold damaged.
- B. Examine walls and ceilings for suitable conditions where lighting control devices will be installed.

- C. Proceed with installation only after unsatisfactory conditions have been corrected.

### 3.2 CONTACTOR INSTALLATION

- A. Comply with NECA 1.
- B. Mount electrically held lighting contactors with elastomeric isolator pads to eliminate structure-borne vibration unless contactors are installed in an enclosure with factory-installed vibration isolators.

### 3.3 WIRING INSTALLATION

- A. Comply with NECA 1.
- B. Wiring Method: Comply with Section 260519 "Low-Voltage Electrical Power Conductors and Cables." Minimum conduit size is 3/4 inch.
- C. Wiring within Enclosures: Comply with NECA 1. Separate power-limited and nonpower-limited conductors according to conductor manufacturer's written instructions.
- D. Size conductors according to lighting control device manufacturer's written instructions unless otherwise indicated.
- E. Splices, Taps, and Terminations: Make connections only on numbered terminal strips in junction, pull, and outlet boxes; terminal cabinets; and equipment enclosures.

### 3.4 IDENTIFICATION

- A. Identify components and power and control wiring according to Section 260553 "Identification for Electrical Systems."
  - 1. Identify controlled circuits in lighting contactors.
  - 2. Identify circuits or luminaires controlled by photoelectric sensors.
- B. Label time switches and contactors with a unique designation.

### 3.5 FIELD QUALITY CONTROL

- A. Perform the following tests and inspections:
  - 1. Operational Test: After installing time switches and sensors, and after electrical circuitry has been energized, start units to confirm proper unit operation.
  - 2. Test and adjust controls and safeties. Replace damaged and malfunctioning controls and equipment.
- B. Lighting control devices will be considered defective if they do not pass tests and inspections.
- C. Prepare test and inspection reports.

### 3.6 ADJUSTING

- A. Occupancy Adjustments: When requested within 12 months from date of Substantial Completion, provide on-site assistance in adjusting lighting control devices to suit actual occupied conditions. Provide up to two visits to Project during other-than-normal occupancy hours for this purpose.
  - 1. For timeclock, verify operation of switch/photocontrol combination. Set time delay to suit Owner's operations. Provide all programming and/or adjustments as required by owner.
  - 2. For daylighting controls, adjust set points and deadband controls to suit Owner's operations.

END OF SECTION 260923