



#### LIGHTING PLAN NOTES:

- 1 EXTEND AND CONNECT EMERGENCY BATTERY FOR EMERGENCY LIGHTING UNITS AND EXITS TO UNSWITCHED HOT LEG OF LIGHTING CIRCUIT IN THE AREA IN WHICH IT SERVES.
- 2 LINE VOLTAGE CEILING MOUNTED OCCUPANCY SENSOR, 2 POLE, SENSORSWITCH #CMR-PDT-9-2P OR APPROVED EQUAL. IF MULTIPLE CONTROLS, THEN WIRE IN PARALLEL SUCH THAT IF ANY SENSOR IS ACTIVATED, THE LIGHTS TURN ON. MANUAL SWITCHING SHALL BE ON THE LOAD SIDE OF THE SENSOR.
- 3 LINE VOLTAGE WALL BOX OCCUPANCY SENSOR, 2 POLE, SENSORSWITCH #WSD-PDT-2P-GY OR APPROVED EQUAL.
- 4 LINE VOLTAGE WALL BOX OCCUPANCY SENSOR/0-10V DIMMER, HUBBELL #LHDMIRS3-N-GY OR APPROVED EQUAL.
- 5 WALL BOX DIMMER, HUBBELL #PSD710-UNV-WYL WITH #PSDKIT-LL-GY COLOR CHANGE KIT. WIRE AS PER MANUFACTURERS INSTRUCTIONS.
- 6 WIRE EXTERIOR LIGHTS VIA 2 CHANNEL ASTRONOMIC DIGITAL TIMECLOCK. WIRE LIGHTING FOR PHOTOCELL ON/TIMECLOCK OFF OPERATION.
- 7 FREEZE PROTECTION WARNING LIGHT, WIRE VIA REVERSE ACTING STAT AND EXTEND TO NEAREST CONVENIENCE OUTLET, SEE POWER PLAN.

